



Voltage Variable Tranformer

หม้อแปลงปรับเปลี่ยนแรงดันไฟฟ้า

Single Phase

www.u-pt.com



Volts Slide Holder



Digital LED & Breaker Protection



Fully Protection



E-VT Series

2kVA - 30kVA

INPUT : 220VAC / 50 ~ 60Hz

OUTPUT : 0 ~ 250VAC / 50 ~ 60Hz

Specification

MODEL	E-VT11 Series						
Power Rating (KVA)	2	3	5	10	15	20	30
Input Voltage	220VAC 1Phase 2Wire 50 / 60Hz						
Output Voltage	0 - 250VAC						
Output Current (Max. A)	6.4	9.6	16	32	48	64	96
Input Protection	By Breaker						
Output Protection	By Breaker						
Indicator	Input Lamp R, S, T, Over Current Buzzer Alarm Digital Output Volt / Amp / Hertz / Meter						
Dimension (W x D x H) Cm	39 x 54 x 33		45 x 53.5 x 35		55 x 57 x 82		50.5 x 55.5 x 122



Applications :

- Lab Test
- Universal Power
- Lighting Dimmer
- Industrial Product
- Electrical Appliances
- Industrial Production Line