



Voltage Variable Tranformer

หม้อแปลงปรับเปลี่ยนแรงดันไฟฟ้า

Three Phase

www.u-pt.com



Volts Slide Holder



Digital LED & Breaker Protection



Fully Protection



E-VT Series

3kVA - 60kVA

INPUT : 380VAC / 50 ~ 60Hz

OUTPUT : 0 ~ 430VAC / 50 ~ 60Hz

(Optional : 0 ~ 500VAC)

Specification

MODEL	E-VT33 Series							
Power Rating (KVA)	3	6	9	15	20	30	45	60
Input Voltage	380VAC 3Phase 4Wire 50 / 60Hz							
Output Voltage	0 - 430VAC / Option : 0 - 500VAC							
Output Current (Max. A)	3.2	6.4	9.6	16	21	32	48	64
Input Protection	By Breaker							
Output Protection	By Breaker							
Indicator	Input Lamp R, S, T, Over Current Buzzer Alarm Digital Output Volt / Amp / Hertz / Meter							
Dimension (W x D x H) Cm	55 x 57 x 82				50.5 x 55.5 x 122			



Applications :

- Lab Test
- Universal Power
- Lighting Dimmer
- Industrial Product
- Electrical Appliances
- Industrial Production Line

