



Voltage Variable Tranformer

หม้อแปลงปรับเปลี่ยนแรงดันไฟฟ้า

Single / Three Phase

www.u-pt.com



Single Phase



Three Phase

E-VTM Series 500VA - 60kVA

Specification

1 Phase Variable Transformer

Input Voltage 220V 50/60Hz Output Voltage 0-250V

MODEL	Output Current (A)	Capacity (kVA)	Dimension / Weight (WxDxH)
E-VTM110.5	1.6AAC	0.5kVA	18x16x16 cm. / 3kg
E-VTM1101	3.2AAC	1kVA	21x23x21 cm. / 6kg
E-VTM1102	6.4AAC	2kVA	21x26x22 cm. / 7.5kg
E-VTM1103	9.6AAC	3kVA	21x27x24 cm. / 10kg
E-VTM1105	16AAC	5kVA	31x26x29.5 cm. / 12.5kg
E-VTM1110	32AAC	10kVA	36x27x47 cm. / 28kg
E-VTM1115	48AAC	15kVA	36x27x61 cm. / 43.4kg
E-VTM1120	64AAC	20kVA	36x27x61 cm. / 46kg
E-VTM1130	96AAC	30kVA	36x28x112 cm. / 90kg

3 Phase Variable Transformer

Input Voltage 380V 50/60Hz Output Voltage 0-430V

MODEL	Output Current (A)	Capacity (kVA)	Dimension / Weight (WxDxH)
E-VTM3303	3.2AAC	3kVA	22x17x42 cm. / 16kg
E-VTM3306	6.4AAC	6kVA	24x21x42 cm. / 22kg
E-VTM3309	9.6AAC	9kVA	25x21x46cm. / 26kg
E-VTM3315	16AAC	15kVA	34x26x62 cm. / 40.5kg
E-VTM3320	21AAC	20kVA	36x27x61 cm. / 44.6kg
E-VTM3330	32AAC	30kVA	36x28x114 cm. / 89kg
E-VTM3345	48AAC	45kVA	40x41x119 cm. / 135.5kg
E-VTM3360	64AAC	60kVA	40x41x119 cm. / 152kg

